

DEMODULATOR FOR DIGITAL RADIO COMMUNICATION

Patent number: JP11098205
Publication date: 1999-04-09
Inventor: NAMEKATA MINORU; KIMURA YASUYUKI
Applicant: TOKYO SHIBAURA ELECTRIC CO
Classification:
- **International:** **H04B7/26; H04L27/22; H04B7/26; H04L27/22;** (IPC1-7): H04L27/22; H04B7/26
- **European:**
Application number: JP19970252486 19970917
Priority number(s): JP19970252486 19970917

Report a data error here

Abstract of JP11098205

PROBLEM TO BE SOLVED: To simplify the configuration by converting a frequency-modulated or phase-modulated signal into an intermediate frequency signal and sampling an output of a counter means operated by a prescribed reference clock, based on a reception signal with an intermediate frequency so as to detect and demodulate phase information, thereby eliminating the need for controlling sign discrimination criterion for each information transmission period. **SOLUTION:** A sampling means 5 is made up of an amplitude limit means 10 that limits an amplitude of the intermediate frequency reception signal outputted from a frequency conversion means 3 and a latch means 21. The latch means 21 is realized by, e.g. a D-type flip-flop 22, its D input terminal connects to an output terminal of a counter means 8, and its CLK input terminal connects to an output terminal of the amplitude control means 10. The D-type flip-flop 22 latches data in m-bit which are phase information of the intermediate frequency reception signal outputted from the counter means 8 at each leading edge of an output signal of the amplitude limit means 10.

